

# BELKIN®

# AC Anywhere™

## DC to AC Power Inverter

### 300 W

### Operate portable AC power devices from your vehicle!

Running out of power is a thing of the past with the AC Anywhere. Simply plug the unit into any 12-volt DC vehicle cigarette lighter socket and the AC Anywhere converts your vehicle's battery power to 230 volts AC (common household current.) The AC Anywhere is perfect for charging batteries for your mobile phone, portable computer, electric shaver, TV/VCR, or virtually any device while travelling. The AC Anywhere inverter features a convenient On/Off switch and fuse protection along with an audible alarm that sounds if the vehicle battery voltage drops to 10.6 volts DC.

#### Specifications:

Model #: F5C412uk300W  
Input Voltage: 12 to 15 Volts DC  
Can not be used with 24 volts (trucks) battery power  
Output Voltage: 240 Volts AC  $\pm$  5%  
Power: 500 Watts - peak  
300 Watts - continuous  
Frequency: 50Hz  $\pm$  3Hz  
Idle Current: Less than 0.2 Amp  
Wave Form: Modified Sine Wave


#### Features:

- 200 mA no-load draw
- Low battery alarm at 10.4V DC
- Low battery shut-off at 9.8V DC
- Automatic overheat shut-off at 66° Celsius
- Negative ground polarity (-)
- DC cord and cigarette lighter plug
- Replaceable fuse (spare included)
- Overload protection
- 2 Year Warranty
- Child Protection built into sockets

P47271uk

Battery Level Indicator Lights

Child Protection built into socket



On/Off Switch

- Recharges portable devices
- Power your mobile and laptop battery chargers
- Power up laptop computers, TVs, VCRs, cameras, and other AC equipment
- Convenient On/Off switch and overload fuse protection
- Low battery alarm and automatic shut-off
- Overload protection