



OmniView™ SOHO Series USB 2-Port and 4-Port KVM Switch with Audio

Control up to four USB computers from one USB keyboard, mouse, and monitor

The new OmniView SOHO Series USB KVM Switch with Audio from Belkin allows you to control up to four USB computers from one USB console. The innovative design provides built-in cable management and saves space while adding a whole new sculpted look to your desktop. Once the shroud slides into place, the cables conveniently flow through the back opening.

The Belkin SOHO Series USB KVM Switch offers advanced engineering, such as audio and microphone support, that enables you to switch between speakers and microphones without having to reconnect. To ensure compatibility with the latest computers and devices, a flash-upgrade feature allows users to update firmware when necessary. Used with coaxial VGA cabling, the Switch supports video resolutions of up to 2048x1536@85Hz through a 400MHz video bandwidth, delivering the highest resolution possible without compromising display quality.



OmniView SOHO Series USB KVM Switches with Audio

Part Number	Description
F1DS102U	2-Port USB Only
F1DS104U	4-Port USB Only

Recommended OmniView KVM Cables for SOHO Series with Audio

Part Number	Description
F1D9101-06	SOHO Series 6 ft., USB Style
F1D9101-10	SOHO Series 10 ft., USB Style

Compatible with USB Mac®, Sun Blade™, and Sun Ray™ computers

Benefits

- Audio and microphone switching support
- Control through USB hot key switching and direct-access port selectors
- Support for USB computers and console
- Support for video resolutions of up to 2048x1536@85Hz
- Built-in cable management
- Flash-upgradeable firmware
- 10-second AutoScan mode to monitor all computers
- Complete USB keyboard and mouse emulation for error-free booting
- Active port LEDs for easy status monitoring
- Belkin 5-Year Warranty and Free Technical Support



Product Specifications

Dimensions:

2-Port:

Height: 6.75"
Width: 4.25"
Depth: 7.75"
Weight: 1.5 lbs.
Enclosure: High-Impact Plastic

Dimensions:

4-Port:

Height: 7.5"
Width: 4.5"
Depth: 9.5"
Weight: 2 lbs.
Enclosure: High-Impact Plastic

Connectors:

Console Connectors:

Keyboard Input: USB "A" type
Mouse Input: USB "A" type
Monitor: HDB15 female
Audio: 3.5mm female
Microphone: 3.5mm Female

Computer: (per port)

Keyboard Input: USB "B" type
Mouse Input: USB "B" type
Monitor: HDB15 Male
Audio: 3.5mm Female
Microphone: 3.5mm Female

Environmental:

Operating Temp: 32°F (5°C) to 104°F (40°C)
Storage Temp: -4°F (-20°C) to 122°F (50°C)
Humidity: 0~80% RH, non-condensing

Power:

9V DC, 1A AC adapter (required)

Supported Hardware:

Computers: USB computers (including Sun workstations and Mac computers with USB)

Monitors:

VGA and SVGA MultiSync®, LCD

Platforms:

Windows® 98, 2000, Me, XP
Linux®
Mac
Sun

LED Indicators:

2 (2-Port), 4 (4-Port)

Warranty:

5 years

The OmniView SOHO Series KVM Switches with Audio, USB platform use standard USB KVM cables. Coaxial VGA cabling is recommended for support of video resolutions of up to 2048x1536@85Hz. The OmniView SOHO Series KVM Switch with Audio, USB platform is compatible with Windows®; 98, 2000, Me, XP, Mac USB and Sun USB platforms, and Linux® distributions.



belkin.com

Belkin Corporation

+1 310 898 1100
Compton • CA • USA

Belkin Ltd.

+44 (0) 1933 35 2000
Rushden • United Kingdom

Belkin B.V.

+31 (0) 20 654 7300
Schiphol-Rijk • The Netherlands

Belkin GmbH

+49 (0) 89 143405 0
Munich • Germany

Belkin Components SAS

+33 (0) 1 34 58 14 00
Jouy en Josas • France

Belkin Ltd.

+61 (0) 2 4372 8600
West Gosford • Australia

© 2004 Belkin Corporation.

All rights reserved. All trade names are registered trademarks of respective manufacturers listed. Mac OS is a trademark of Apple Computer, Inc., registered in the U.S. and other countries.